

User manual
mermaid ventura 170 TFT
Analog Only Model



Table of Content:

Table of Content:	2
1. Preface	3
2. Important Information	3
3. Content of the Box	4
4. Unpacking, Placement and Set-up (PC)	4
5. OSD Key Functions	4
6. OSD Functions & Adjustments	6
7. Guarantee Terms	10
8. If you need to contact us!	10
9. Troubleshooting	11
Appendix A: Connector Specifications	12
Appendix B: Power Management Mode: VESA DPMS protocol applied	13
Appendix C. Technical Specifications	14
Appendix D: Video Mode Support	16
Appendix E: Optical Characteristics – ventura 170 TFT	17

1. Preface

The mermaid ventura 170 TFT is a state of the art high-tech flat panel TFT monitor, including a high quality TFT-LCD panel with maximum resolution of 1280x1024 @75 Hz, based on the newest TN technology, and high brightness 4-lamp CCFL backlight unit. The very fast response time (typ. 25 ms) provides excellent suitability for video and gaming applications. The monitor is made of steel and hardened glass which provides excellent stability and strength. The integrated hinge and high adjustment means you are able to manoeuvre the monitor for optimal viewing angle and comfort. The monitor is fully DDC 2 compliant, which makes installation very easy.

Connections:

- Analog VGA (D-Sub connector via integrated cable)

Features:

- Graphical based OSD menu controlling all the functions of the monitor.
- High display quality : High contrast ratio, wide-viewing angle and High-speed response time.
- High brightness with the 4-CCFL backlight lamps
- Intelligent Digital Image processor
- Wide Input Voltage Range +10 VDC - +15 VDC
- Accepts refresh rates of between 56 Hz and 75 Hz.
- VESA DPMS power saving compatible.
- DDC Ver.2 Compliant
- Low power Consumption (typ. 32 Watts)
- Sync: separate H/V Sync, Polarity pos. or neg.

2. Important Information

When using the ventura 170TFT with Windows NT, it is recommended that the refresh rate be set to 60 Hz before connecting the monitor.

Please save the packaging. It has been designed to provide optimal support and protection for the monitor during transportation.

3. Content of the Box

- ventura 170 TFT (17")
- "Quickstart" card

Accessories bag including:

- PSU (45 Watt)
- Powercord
- Speaker cable
- Users manual
- Glass cleaner & screen wiping cloth

4. Unpacking, Placement and Set-up (PC)

After the box has been opened, remove the accessories bag.

Bend the cardboard flaps outward and turn the box upside down, which will ensure the inlay foam with the monitor is able to slide out. Do not drop the content on the floor.

Remove the foam side pieces and the plastic bag.

The monitor needs to be placed on a smooth and stable surface. This surface must be able to safely support 15 kg.

Make sure both the computer and monitor are turned off before connecting the monitor.


- Connect the monitor to the computer by means of the supplied VGA cable. (Attached to the monitor)
- Connect the PSU to the monitor and AC outlet.
- Turn on the computer and monitor.

OSD panel is located
beneath the monitor



- mermaid ventura 170 TFT is plug & play compatible via VESA DDC1/2B. Windows 98, ME and XP will recognise this and self configure.
 - When using the mermaid ventura 170 TFT with Windows NT, the computer needs to be started in VGA mode the first time. Log on as administrator and set the resolution to 1280x 1024 and refresh rate to 60 Hz. The computer can then be started in normal mode.
-

5. OSD Key Functions



Hot Key	Menu	Bright	Bright	Source Info
Normal	Select	Down Left	Up Right	Exit Pre-Menu

Function	Description
Menu (Hot Key)	Activate the OSD
Bright (Hot Key)	Activate brightness control OSD
Source info (Hot Key)	Displays the resolution and frequencies of the input
Select	Select the highlighted menu
Down/Left Up/Right	Moves the selector right or left on the OSD Increase or decrease the value of the selected item.
Exit	Exit from menu or sub-menus Exit from OSD menu

6. OSD Functions & Adjustments



Function


Description

1. Brightness


Changes the overall brightness of the image.

2. Contrast

Changes the ratio between white and black.



☺ Distinct




☹ Vague


3. Phase

Fine tune vertical and horizontal noise in the display.

4. Frequency



Mismatch of Horizontal image size causes periodic vertical bands in the display



Mismatch of Phase causes Horizontal line noise in the display

5. H-Position

Moves the vertical and horizontal location of the picture shown.

6. V-Position

7. Sharpness

Modify the sharpness of the display.

Sharp: Edges of image become sharp

Medium

Soft: Edges of image become soft

8. Color Temperature

Changes the color tone of the display.

OSD Functions & Adjustments - continued




Function	Description
1. H-Position	Moves the location of the OSD menu.
2. V-Position	
3. OSD Timeout	Specifies the time span before the OSD menu disappears. (20 - 200 seconds)
4. Language	Specifies the OSD language. Select between English – German – Korean and Japanese

OSD Functions & Adjustments - continued



Function	Description
1. Dynamic Brightness	Smart Inverter Control. This function allows the system to adjust the brightness of the backlight automatically in conjunction with the quantity of the input data.
2. Information	Displays the resolution and frequencies of the input.
3. Reset	Reset to factory default.
4. Half Tone	Changes the color of the OSD menu.

OSD Functions & Adjustments - continued



Function	Description
Auto Adjust	The built-in microprocessor will optimize all display adjustment sets such as video offset gain, position, phase and frequency automatically according to the pre-programmed auto adjustment program. 1)

- 1) If the microprocessor does not optimize all settings successfully, please use the manual adjustment functions in the OSD menu. (Phase – Frequency – V-position and H-position)

7. Guarantee Terms

mermaid ventura 15" are covered by a 3-year guarantee agreement (1 year SWAP + 2 years Pick-UP).

SWAP

Exchange at your address. If your mermaid ventura needs repairing, contact mermaid customer services, who will arrange to have your screen exchanged for a new one within 5-7 working days.

Pick-UP

Collection from and return to your address. If your mermaid ventura needs repairing, contact mermaid customer services, who will arrange to have your screen collected, repaired and returned to you within 14 working days.

The guarantee terms set out above apply to Europe only.

8. If you need to contact us!

Contact mermaid customer support

If you need to get in touch with mermaid technology, please contact us via phone or mail:

Phone

mermaid customer support opening hours are Monday to Friday 12.30-16.30.

By mail

mermaid technology a/s
Att.: Customer Support (Kundeservice)
Symfonivej 34-36
2730 Herlev
Denmark

Telephone

+45 44 52 92 00

Telefax

+45 44 52 92 65

E-mail

kundeservice@mermaid.dk

Internet

<http://www.mermaid.dk>


9. Troubleshooting

If you have troubles using this monitor, please refer to following suggestions for troubleshooting.
If you can not rectify the problem yourself, please contact your distributor or place of purchase.

Symptom	Suggestions
Screen is blank	Ensure that the power cord is connected and the monitor is on.
"Check signal cable" message	Ensure that the signal cable is connected firmly to the signal source. Ensure that the signal source is turned on.
"Sync out of range" message	Check the maximum resolution and the frequency of the video adapter.
The image is too dark or bright	Adjust the brightness and contrast.
Horizontal bars appear to flicker, jitter or shimmer on the image	Adjust the "Phase".
Vertical bars appear to flicker, jitter or shimmer on the image	Select "Auto Adjust" in OSD menu
Screen is blank	The system activates power management mode. Just press the PC keyboard or move the PC mouse
Image is not stable and may appear to vibrate	Check the display resolution and frequency from your PC or video board is within the available range of your monitor. On your PC, check "Control Panel -> Display >Settings". If the setting is incorrect, you may change the setting using PC utility program.
Image is not centered on the screen	Adjust the "Image Position / H-Position or V-Position".

Appendix A: Connector Specifications

Analog RGB in



Pin no.	Function	Pin no.	Function	Pin no.	Function	Pin no.	Function
1	Red	2	Green	3	Blue	4	NC
5	GND	6	R_GND	7	G_GND	8	B_GND
9	NC	10	GND	11	GND	12	SDA
13	H Sync	14	V. Sync	15	SCL		

Appendix B: Power Management Mode: VESA DPMS protocol applied

Mode	Horizontal sync	Vertical sync	Video signal	Power Consumption
On	Active	Active	Active	32 watts (typ.)
Stand by	Inactive	Active	Blanked	< 3 Watts
Suspend	Active	Inactive	Blanked	
Off	Inactive	Inactive	Blanked	

Appendix C. Technical Specifications

Input Video and sync signal

Item		Description	Notes
Video	Input	<ul style="list-style-type: none"> Type: Analog RGB Level: 0.7Vp-p $\pm 5\%$ Polarity: Positive Bright Impedance: $75\Omega \pm 5\%$ (Terminated) 	VESA Compliance
	Resolution	<ul style="list-style-type: none"> Optimum: 1280x1024@60Hz Maximum: 1280x1024@75Hz 	
	Horizontal Frequency	<ul style="list-style-type: none"> 30-80KHz 	
	Vertical Frequency	<ul style="list-style-type: none"> 55-75Hz 	
	Applicable Bandwidth	<ul style="list-style-type: none"> Typical: 108MHz (1280x1024@60Hz) Max: 135MHz (1280x1024@75Hz) 	
	Sync Signal	<ul style="list-style-type: none"> Type: Separate H/V sync, Composite H/V Sync, Sync-on-green (SOG) Level: TTL level (V high $\leq 2.0V$, V low $\leq 0.8V$) Polarity: Positive or negative Termination resistance: more than $2K\Omega$ 	
Sync	Input	<ul style="list-style-type: none"> Type: Separate H/V sync Level: TTL level (V high $\leq 2.0V$, V low $\leq 0.8V$) Polarity: Positive or negative 	

Electrical Parameters

Description	Min	Typ	Max	Unit
DC power supply	10	12	15	Volts
Supply Current (Vcc=12Volt)		2.0	2.3	Amp.

Additional parameters

Description	Value	Unit	
Driver element	a-Si TFT active matrix		
Display Colors	16.7M (true)	Colors	
Display area	337.92(H) x 270.336(V)	mm	17.0 Inch diagonal
Number of Pixels	1280 x 1024	Pixels	
Pixel arrangement	RGB vertical stripe		
Pixel Pitch	0.264(H) x 0.264(W)	mm	
Display Mode	Normally White		
Lamp	4-Lamp CCFL		
Operating temperature	0 ~50	°C	
Storage temperature	-25 ~60	°C	

Appendix D: Video Mode Support

No	Mode	Resolution	Total	Horizontal		Vertical		Pixel Clock
				Frequency	Polarity	Frequency	Polarity	
1	VGA	720x400	900x449	31.47KHz	N	70.0 Hz	P	28.322MHz
2		640x480	800x525	31.47KHz	N	60.0 Hz	N	25.175MHz
3		640x480	864x525	35.00KHz	N	66.7 Hz	N	30.240MHz
4		640x480	832x520	37.86KHz	N	72.8 Hz	N	31.500MHz
5		640x480	840x500	37.50KHz	N	75,0 Hz	N	31.500MHz
6	SVGA	800x600	1024x625	35.16KHz	N/P	56.3 Hz	N/P	36.000MHz
7		800x600	1056x628	37.88KHz	P	60.3 Hz	P	40.000MHz
8		800x600	1040x666	48.08KHz	P	72.2 Hz	P	50.000MHz
9		800x600	1056x625	46.87KHz	P	75.0 Hz	P	49.500MHz
10		832x624	1152x667	49.73KHz	N	74.6 Hz	N	57.284MHz
11	XGA	1024x768	1344x806	48.36KHz	N	60.0 Hz	N	65.000MHz
12		1024x768	1328x806	56.48KHz	N	70.1 Hz	N	75.000MHz
13		1024x768	1312x800	60.02KHz	P	75.0 Hz	P	78.750MHz
14	SXGA	1280x1024	1688x1066	64.00KHz	P	60.0 Hz	P	108.000Mhz
15		1280x1024	1688x1066	80.00KHz	P	75.0 Hz	P	135.000Mhz

Appendix E: Optical Characteristics – ventura 170 TFT

The following items were measured under stable conditions. The optical characteristics should be measured in a dark room or equivalent state.

* Measuring equipment: TOPCON MB-5A: Contrast Ratio, Luminance of White, Viewing Angle
 TOPCON BM-7: Response time
 Photo Research PR650: Color Chromaticity

* $T_a = 25 \pm 2 \text{ }^\circ\text{C}$, VIN = +12V fv= 60Hz

Item	Symbol	Condition	Min.	Typ.	Max.	Unit	
Contrast Ratio	CR		250	350	-		
Response Time at T_a	Rising	T_R	-	5	15	msec	
	Falling	T_F	-	20	30		
Luminance of White (Center of Screen)	Y_L	$\ddot{O}=0,$ $\ddot{E}=0$	200	250	-	cd/m ²	
Color Chromaticity (CIE 1931)	Red	R_X	-0.03	0.631	+0.03		
		R_Y		0.354			
	Green	G_X		0.294			
		G_Y		0.596			
	Blue	B_X		0.143			
		B_Y		0.087			
	White	W_X		0.300			
		W_Y		0.340			
Viewing Angle	Hor.	\dot{e}_L	CR 10	60	65	-	Degrees
		\dot{e}_R	60	65	-		
	Ver.	\dot{E}_H	50	55	-		
		\dot{E}_L	50	55	-		
Color Gamut			-	65	-	%	
Brightness Uniformity (9 points)	B_{UNI}		-	-	25	%	
Cross Modulation	C_T		-	-	5	%	

- Measuring Condition: Maximum value of Brightness and Contrast in OSD menu.